

UL CODE STATION

APPLICATION

The SF-156B (SF156B) Code Station is used to operate all system code signals (except supervised code blue applications). It may be used independently or connected with other call stations or intercom stations.

Placing a code call is accomplished by pulling the slideswitch located at the center of the panel to the down position. Returning the slide-switch to the up position cancels the call.

FEATURES

- UL® 1069 Listed
- Simple, reliable operation
- Call-placed indicator
- Call activates light on annunciator panel, corridor light and/or zone light
- Mounted on attractive flame retardant (UL® 94V-0) plastic panel
- Corridor zone light capability

SPECIFICATIONS

Dimensions: Height: 4.50" (114 mm)
Width: 2.75" (69 mm)
Depth: 0.75" (20 mm)

Construction: Reliable components mounted on an attractive flame retardant (UL® 94V-0) plastic panel.

Connections: Plug-in wiring pigtail.

Housing: Single gang ring (or single gang ring/ double gang box)

REQUIRED COMPONENTS

Tek-CARE® NC-110 Nurse Call System
PK-153 Third Priority Control Unit



SF-156B
CodeStation

ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

Code station shall be TekTone® SF-156B or approved equal as supplied by LEE DAN®.

Operation of all system code signals shall be accomplished by activating the centrally-located slideswitch. Call placement is indicated by a rapid flashing red light. Canceling the call shall be possible only at the point of origin. Reliable solid-state components shall be used.

A plug-in wiring pigtail shall be provided for all connections. The SF-156B shall be used in conjunction with a PK-153 third priority control unit to provide a separate and distinct flash and tone rate.

The SF-156B shall be UL® 1069 Listed.