

2-BUTTON APARTMENT STATION

APPLICATION

The IR102C (IR-102C) Suite Station allows the tenant to press a button to talk and then release the same button to listen. This eliminates the necessity of pressing one button to talk and another button to listen.

The station automatically shuts off a few seconds after conversation is completed, or as soon as the door button is pressed. The IR102C is not a voice/noise activated intercom station and does not require a complex and costly amplifier.

FEATURES

- One combination **TALK/LISTEN** button
- Eliminates two-button talk/listen operation
- Uses standard amplifier power pack
- English text, international symbols and Braille

SPECIFICATIONS

Dimensions: Height: 6.875" (174.6 mm)
Width: 5" (127 mm)
Depth: 1.5" (38.1 mm)
Projects: 1" (25.4 mm) from mounting surface

Finish: Molded of high-impact ABS plastic

REQUIRED COMPONENTS

Panel/Styles Vary *LEE DAN*® or TekTone® Entry Panel
PK-543A Intercom Amplifier
PS-3A, PS-20A Transformer
IH-102, IH-101 Flush Ring or Flush Housing
IH-400A Desk Cabinet
IH-700 Surface Back Box



IR-102C
2-Button Apartment Station

ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

Suite station shall be TekTone® IR102C (IR-102C) or approved equal, as supplied by *LEE DAN*®, and shall provide circuitry for communications, signaling, and door release operation.

Talk and listen functions shall require operation of a single push button. The speaker shall be a voice frequency response type. Electronics shall be securely mounted on a printed circuit board. Wiring shall be via screw terminals.